



# 4-Battery Power Station Box

## S-4010/S-4020/S-4030

- ◆ Install 4x V-mount batteries
- ◆ 2x XLR DC output (12V or 24V option)
- ◆ Real time output voltage LED display
- ◆ Low battery warning
- ◆ Charging without take out batteries
- ◆ Intelligent protective circuit design
- ◆ PP + Fiber glass case, strong and durable



PP + Fiber glass case



Install 4x V-mount batteries



Inside charging (5A)



Voltage display / alert

## Output Descriptions:



**S-4010** 12v + 12v  
Dual 12V output

4-pin XLR 11-16.8V DC output x2  
Max Load: 15A/180W per channel  
2 channels output simultaneously



**S-4020** 12v + 24v  
12V + 24V output

4-pin XLR 11-16.8V DC output x1  
Max Load: 15A/180W  
3-pin XLR 22-33.6V DC output x1  
Max Load: 15A/360W  
12V and 24V will not output simultaneously



**S-4030** 24v + 24v  
Dual 24V output

3-pin XLR 22-33.6V DC output x2  
Max Load: 15A/360W in total  
2 channels output simultaneously

## Specification

Model	S-4010	S-4020	S-4030
Input	DC 16.8V 5A (Charging)	DC 16.8V 5A (Charging)	DC 16.8V 5A (Charging)
Output	DC11-16.8V 15Ax2 (180Wx2)	DC 11-16.8V 15A (180W) Or DC 22-33.6V 15A (360W)	DC 22-33.6V x2 Total 15A(360W)
Dimension	290mm x 221mm x 278mm		
Net weight	3.45Kg		
Working environment	Working temperature: 0°C ~ +40°C Working humidity: 10% ~ 90% Storage temperature: -15°C ~ + 60°C		

**SWIT Electronics Co., Ltd.**

Website: [www.swit.cc](http://www.swit.cc) Tel: +86 25 85805753

Email: [contact@swit.cc](mailto:contact@swit.cc) Fax: +86 25 85805296

**Distributed by:**